

WIFI 防蹭网

1、设置防蹭网的 IP 地址范围

WIFI 设置 — WIFI 防蹭网 — 地址池，点击<添加>。

在弹出的 【添加新地址】 窗口中设置开启防蹭网的 IP 范围。

添加新地址

* 起始IP

192.168.1.100

* 终止IP

192.168.1.200

启用状态

启用

备注

WIFI用户

取消

提交

起始 IP：192.168.1.100（WIFI 起始 IP）

终止 IP：192.168.1.200（WIFI 结束 IP）

启用状态：启用

备注：WIFI 用户（备注内容）

点击<提交>，防蹭网 IP 地址范围添加成功。

2、 启用 WIFI 防蹭网功能

WIFI 设置 — WIFI 防蹭网 — 基础配置

启用状态	<input checked="" type="checkbox"/> 启用 <input type="checkbox"/>
PC在线检测周期	<input type="text" value="0"/>
账号最大在线时长	<input type="text" value="0"/>
绑定账号共享数	<input type="text" value="0"/>
* 管理员WIFI账号	<input type="text" value="admin:admin"/>
<input type="button" value="提交"/>	

启用状态：启用

PC 在线检测周期：0（检测获取 WIFI 账号的 PC 是否在正常使用状态的间隔时间）

账号最大在线时长：0（获取到的 WIFI 账号上网时间）

绑定账号共享数：0（获取到的 WIFI 账号允许同时使用设备的数量）

管理 WIFI 账号：admin:admin（WIFI 管理账号，格式为“账号:密码”）

点击<提交>，WIFI 防蹭网功能设置完成并启用。

3、获取 WIFI 上网账号

在客户机用浏览器打开链接 <http://路由 IP/AC/wifi.html> 获取用户密码，也可以使用浏览器扫描页面的二维码上网。

WIFI 上网动态密码获取如下图：



说明：

- 1、一旦动态密码的页面关闭，密码即刻失效；
- 2、通过扫描二维码上网的时候，请尽量使用浏览器来扫描二维码；

附手机登录验证界面，如下图：



The image shows a mobile application interface for WiFi login. At the top, there is a status bar with the time 19:56, signal strength, 1.13% battery, and a 18% battery icon. Below the status bar is a header area with the text "无线手机登陆" (Wireless Mobile Login) and a refresh icon. The main content area has a dark background with the Netzone logo (a blue and green cube) and the text "网纵 NETZONE". Below the logo, the text "WIFI登录" (WiFi Login) is displayed. There are two input fields: "用户名" (Username) and "密码" (Password). Below these fields is a large orange button labeled "提交" (Submit). At the bottom of the screen, there is a navigation bar with icons for back, forward, a tab labeled "1", home, and more options.

19:56 1.13% 18

无线手机登陆

网纵
NETZONE

WIFI登录

用户名

密码

提交